

Release Notes

LCOS FX

11.1 RU1

Table of contents

02	1. Preface
02	2. The release tag in the software name
03	3. Supported hardware
04	4. History LCOS FX
04	LCOS FX improvements 11.1 RU1
06	LCOS FX improvements 11.1 Rel
08	LCOS FX improvements 11.1 RC1
10	5. Further information
10	6. Disclaimer



1. Preface

The LANCOS family of operating systems—LCOS, LCOS SX, LCOS LX, and LCOS FX—forms the trusted basis for the entire LANCOS range of products. Within the scope of the hardware specified by the products, the latest firmware version is available for all LANCOS products and is offered by LANCOS Systems for download free of charge.

This document describes the innovations within software release LCOS FX 11.1 RU1.

2. The release tag in the software name

Release Candidate (RC)

A Release Candidate has been extensively tested by LANCOS and includes new LCOS features. It is suitable for testing and is not recommended for use in productive environments.

Release Version (REL)

The release version has been extensively and successfully tested in practice. It contains new features and improvements over previous LANCOS operating system versions and is therefore recommended for use in productive environments.

Release Update (RU)

A release update is a further development of an initial release version in productive environments and contains minor improvements, security fixes, bug fixes and smaller features.

Security Update (SU)

Contains important security fixes for the respective LANCOS operating system version and ensures that your security level remains very high on an ongoing basis in your productive environment.



3. Supported hardware

Version 11.1 RU1 supports the following hardware appliances:

- LANCOM R&S®Unified Firewalls
 - UF-50/60/60 LTE/T-60/100/160/200/260/300/360/500/760/900/910/1060
- R&S®UF-50/100/200/300/500/800/900/1000/1200/2000
- R&S®UF-T10
- R&S®UTM+100/200/300/500/800/1000/2000/2500/5000
- R&S®NP+200/500/800/1000/2000/2500/5000
- R&S®GP-U 50/100/200/300/400/500
- R&S®GP-E 800/900/1000/1100/1200
- R&S®GP-S 1600/1700/1800/1900/2000
- R&S®GP-T 10

Version 11.1 RU1 supports the following virtual appliances:

- LANCOM vFirewall S, M, L, XL
- R&S®UVF-200/300/500/900

Version 11.1 RU1 supports the following hypervisors:

- VMware ESXi
- Microsoft Hyper-V
- Oracle VirtualBox
- KVM

4. History LCOS FX

LCOS FX improvements 11.1 RU1

New features

→ TCP Load Balancer

TCP load balancers can be used to distribute any TCP connection to several backend servers behind the firewall. Thanks to active server monitoring, connections are only ever forwarded to functional servers.

Bugfixes

- After an update to LCOS FX 11.1 Rel, the Unified Firewall used port 0 instead of the standard port 22 for the automatic backup via SCP. As a result, the automatic backup no longer worked.
- If a network was created that should use a GPON interface, an error message was displayed when selecting the interface, stating that the selected interface was already being used in a bridge. As a result, no connection could be configured.
- If a static IPv6 WAN connection was active on a Unified Firewall, the DNS function no longer worked for DHCPv4 connections configured on the same interface.
- In LCOS FX 11.1 Rel, it could happen that a timeout occurred when creating a reverse proxy entry with LetsEncrypt when creating the LetEncrypt certificate. This could also occur when renewing a certificate via the web interface.
- If there were a large number of entries in the reverse proxy list and these were made available via the external web interface, some entries could not be displayed there because scrolling was not possible.
- The LMC device certificate saved during the backup of an LMC-managed Unified Firewall is only transferred during the re-import if there is no LMC device certificate in the Unified Firewall.
- After updating to LCOS FX 11.1 Rel, the data of the updated device was no longer displayed in the Command Center.
- No default route was created for a configured DHCPv6 WAN connection. As a result, the connection was not functional.
- After setting up an Internet connection with IPv6 and address assignment via DHCP, the default route was no longer available after restarting the Unified Firewall. As a result, communication with the Internet via IPv6 was no longer possible.
- Groups that contained other groups with users (nested groups) were not supported by the SAML implementation and could therefore not be synchronized.

- When assigning a VLAN interface to a DHCPv6 connection, the error message “The connection type is invalid for the selected interface.” was displayed. As a result, the connection could not be saved.
- If a user tried to access the stored website without authorization for the reverse proxy frontend, a redirect to the login page took place. The login page was reloaded again and again.
- If the ‘Synchronize now’ button was clicked after configuring the SAML parameters without first saving the configuration, this had no effect. By clicking on the ‘Synchronize now’ button, the configuration is now validated and saved and the synchronization is then carried out.
- On a LANCOM Unified Firewall UF-60 LTE it could happen that processes were not terminated correctly and the memory was not released. This led to an immediate restart of the Unified Firewall.
- The encryption algorithms used in the security profile ‘LANCOM LCOS Default IKEv2’ did not match the default settings in LCOS. As a result, when using this profile, VPN connections with LANCOM routers with LCOS and with the LANCOM Advanced VPN Client did not work or the connection was interrupted.
- If a DHCP relay sent data via a VPN connection whose Internet connection obtained the IP parameters via PPP, the DHCP relay no longer worked after a restart of the Unified Firewall.
- In a shaping configuration for traffic shaping, entered values were displayed multiplied by 1000 after saving (e.g. 5 Mbit entered, 5,000 Mbit displayed). This was merely a display error.
- If the option ‘Block incorrectly scanned files’ was active in the antivirus settings (default setting), it could sporadically happen that even correctly scanned websites without malware were blocked by the antivirus engine. The error message “The request has been blocked. The requested URL could not be retrieved due to an anti virus engine failure.” was displayed.

LCOS FX improvements 11.1 Rel

Improvements

- In addition to traffic groups, traffic shaping can also be set directly for source interfaces.
- Performance optimization of the reverse proxy
- The engine for application filter and application-based routing recognizes doctolib.

Bugfixes

- In the alarm and system log of the firmware version LCOS FX 11.1 RC1, the name of the detected virus was not displayed in an antivirus incident.
- If the antivirus option 'Block files if scan fails' was deactivated in firmware version LCOS FX 11.1 RC1, password-protected files were still blocked by the Unified Firewall.
- On the notification page for a detected virus, the name of the detected virus was not included for firmware version LCOS FX 11.1 RC1.
- After renaming a VPN SSL connection, the 'Activate' button in the menu bar of the Unified Firewall was not colored blue.
- No description text was displayed in the host / network groups in firmware version LCOS FX 11.1 RC1 if objects were added that were not in the list.
- After a Unified Firewall was reset to factory settings via the web client, no more settings could be made in the LetsEncrypt configuration dialog.
- In LCOS FX 11.1 RC1, not all buffer contents were taken into account for IDS / IPS. As a result, some data traffic was not checked by IDS / IPS.
- The IP protocols 61, 63, 68, 99, 114, and 253 have not been assigned a name in the user-defined services. Furthermore, a manually entered service name was not transferred to the menu bar.
- A proxy exception configured in LCOS FX 11.1 RC1 for a specific website in a routing profile for application management was not applied. This resulted in the website being blocked by the content filter.
- It was not possible to create an additional administrator in the Unified Firewall via an LMC add-in. The rollout was acknowledged with the error message "None Type has no attribute username".
- If the 'suricata' service (responsible for the IDS / IPS) was terminated abruptly, local services such as DNS could be accessed and used externally.
- An IPv6 address stored in LCOS FX 11.1 RC1 for the default gateway was not displayed in the status information of the Internet object.
- When using the HTTP(S) proxy with activated Antivirus, it could happen sporadically that websites were blocked.

- It is now possible to activate an automated restart of the HTTP(S) proxy at midnight via script. Please contact LANCOM Support to receive the script file.
- When creating a management report with the Unified Firewall, the number of packets blocked by IDS / IPS was not displayed graphically in the diagram.
 - If a DHCP relay server was stored for an interface on a Unified Firewall and then another entry was stored for another interface with a different DHCP server, only the new entry worked.
 - If a user-defined service was created in firmware version LCOS FX 11.1 RC1 and only one source port was to be specified, this did not work if only a port number was entered in the 'Source port from' field and the 'To' field remained empty.
 - No host names could be stored in the DNS server settings. As a result, it was not possible to store the host name 'wlc-address', for example.
 - If the reverse proxy was very heavily utilized, it could happen that the reverse proxy stopped forwarding packets after some time.
 - The SSO client (Single Sign On) could no longer connect to the Unified Firewall with LCOS FX 11.1 RC1 because port 6789 was blocked by the packet filter. As a result, Single Sign On no longer worked.
 - In the LCOS FX 11.1 RC1 firmware, the mail proxy did not work with the default certification authority.
 - With LCOS FX 11.1 RC1, it could happen in an HA cluster that the PostgreSQL database on the backup firewall was no longer functional. This caused the synchronization of the log database between the master and backup firewall to stop. Furthermore, the hard disk of the backup firewall was filled up.

LCOS FX improvements 11.1 RC1

New features

→ IPv6 WAN

The firewall can be operated on pure IPv6 connections or mixed IPv4/IPv6 connections. IPSec VPN tunnels and Wireguard VPN tunnels can be set up via IPv6. In addition, reverse proxy frontends can be offered via IPv6 and the firewall's web client and SSH can be accessed via IPv6.

→ SAML authentication

In addition to local users and the LDAP connection, the firewall can use SAML authentication to authenticate users for user- or group-specific rules. Keycloak and Microsoft Entra ID are supported as IDP.

→ Reverse proxy authentication

Services offered by the firewall via the reverse proxy can be restricted to certain users or groups. Local as well as LDAP and SAML users and groups are supported.

→ HA cluster handover in the event of a network interface failure

If a network interface on the active cluster node fails, the other firewall takes over, provided the interface on the second machine is working.

→ New anti-virus engine

Bitdefender will be used for the anti-virus functionality, as it has already been for anti-spam and Content Filter.

→ REST API documentation via OpenAPI

The REST API of the configuration interface is documented using OpenAPI. The documentation can be viewed live via the browser.

→ Support for general IP protocols

With user-defined services, it is possible to create services for any IP protocols.

→ User-defined services with restriction of the source port

With user-defined services, it is also possible to restrict the permitted source ports for TCP- or UDP-based services.

Improvements

- The UF-260 supports the GPON module LANCOM SFP-GPON-1.
- On the 'rules' desktop, groups can refer directly to network and host objects in order to avoid double configuration of IP addresses.
- The reverse proxy now supports websockets.
- A timeout towards the backend server can be configured for the reverse proxy.
- HostHeader Preservation can be configured for the reverse proxy.

- Any ACME server is supported.
- It is possible to bind reverse proxy frontends to Wireguard connections.
- It is possible to bind the external portal to Wireguard connections.

Further information

- The VoIP proxy has been removed.
- The import of configuration backups is only supported from version 9.8.
- Please note that the reverse proxy is not included in a Basic license. Use of the Reverse Proxy within the Basic license is therefore outside the contractual scope of the license. As of version 11.1, it will no longer be possible to use the Reverse Proxy with the Basic license. Please perform an upgrade to a Full license in time, so that the Reverse Proxy can still be used.
- The Outlook Anywhere option of the reverse proxy has been removed, as it is no longer required for current Microsoft Outlook / Exchange versions.

Bugfixes

- A user with "Read-Only" authorization could not export the backup or a VPN-SSL connection.
The export of the backup and the export of a VPN SSL connection is now also possible with "Read-Only" authorization.
- If a Unified Firewall with active IDS/IPS was shut down unexpectedly (e.g. due to a power failure), the connection tracking service (conntrackd) could no longer start. As a result, IDS/IPS no longer functioned. Furthermore, a sudden restart could occur when IDS/IPS tried to access the connection tracking service.
- The Netfilter service (nftd) tried to write the firewall rules again and again, which resulted in increased RAM utilization. This could also lead to firewall rules not being written.
- When using multi-WAN weighting with multiple Internet connections, the Internet connections were not prioritized correctly and the majority of traffic was sent over the connection with the lower weighting.
- In an HA cluster, sporadic packet losses could occur during communication via the firewall.

5. Further information

- Backups of versions 9.8 und 10.X are supported.
- Devices with less than 4 GB of RAM can not execute all UTM features simultaneously.

6. Disclaimer

LANCOM Systems GmbH does not take any guarantee and liability for software not developed, manufactured or distributed by LANCOM Systems GmbH, especially not for shareware and other extraneous software.

